FDV3-W

Data Communication Protocol Specification - 2.4G Wi-Fi

Product Manual (Ver.1.1)



Content

MQTT Data Format Description（V1.1） 1

1. Overview 1

2. Device Function Properties 1

Device Online/Offline Status（online） 1

Initialization Complete（initFinish） 1

Heartbeat（heartBeat） 2

Product Model（productMode） 2

Product ID（productId） 3

Hardware Model（hardwareModel） 3

WIFI Firmware Version（firmwareVersionWiFi） 4

Firmware Version（firmwareVersion） 5

Firmware Version（firmwareVersionProduct） 5

Install Height（installHeight） 6

Position Out-of-Bounds Status（locationOutOfBounds） Not Available Currently 7

Human Detection Function Switch（humanSwitch） 8

Human Presence Status（someoneExists） 9

Human Motion Status（motionStatus） 10

Movement Signs Parameters（movementSigns） 10

Sitting Horizontal Distance（sittingHorizontalDistance） 11

Motion Horizontal Distance（horizontalDistanceOfMovement） 12

Human Presence Judgment Method（humanExistenceJudgmentMethod） Currently unavailable; reserved for future use. 13

Human Presence Detection Threshold（humanPresenceJudgmentThreshold） 14

Human Presence Energy Value（humanPresenceEnergyValue） 15

Human Energy Value Switch（humanEnergyValueSwitch） 15

No Presence Duration（unmannedTime） 16

Fall Height Threshold（fallingAndBreakingHeight） 17

Fall Switch（fallSwitch） 18

Fall Status（fallStatus） 19

Stationary Presence Status（residentStatus） 20

Stationary Presence Duration（residentWarningDuration） 21

Stationary Presence Detection Switch（residentWarningDurationSwitch） 22

Fall Duration（fallDuration） 23

Voice Function Switch（US518FunctionSwitch） 24

Voice Learning Mode (US518LearningFunction) 25

Night Light Control Switch（nightLightSwitch） 26

Custom Protocol（custom_protocol） 27

3. Restricted Function Property Reporting 28

4. QoS (Quality of Service) Settings 29

5. OTA Update 30

OTA Module Update（otaModule） 30

OTA Update Information（otaInform） 31

Update Progress（downloadProgress） 31

6. Historical Version Update Notes 32

MQTT Data Format Description（V1.1）

1. Overview

This document describes the MQTT data communication protocol for the FDV3-W Human Presence and Fall Detection Device. It explains how to obtain device data and control device functions, enabling developers to integrate and use the device efficiently. All data is transmitted in JSON format.

The Human Presence and Fall Detection Device uses two MQTT topics (**the Device ID is unique**), as described below:

（1）Topic：/Radar60FL/Device ID/sys/property/post

Publish Topic − Used by the device to publish sensor data and responses to configuration commands.

（2）Topic：/Radar60FL/Device ID/sys/property/set

Subscribe Topic − Used by the client to publish commands to the radar device.

2. Device Function Properties

Device Online/Offline Status（online）

Reporting Method: Active reporting.

The property status is defined as follows:

- 0: Offline
- 1: Online

The device actively reports this property whenever its status changes.

```
{
        "version":"1.0",
        "method":"post",
        "params": {
                    "online":  "0"
        }
}
```

Initialization Complete（initFinish）

Reporting Method: Not supported for active reporting.

Data range:

- 0: Initialization not complete
- 1: Initialization complete

This property supports querying. The query format is as follows:

```
{
    "version":"1.0",
    "method":"get",
    "params": {
            "initFinish":       "?"
    }
}
```

Query response format is as follows:

```
{
    "version":"1.0",
    "opt":      "get",
    "res":      "success" //"fail" when the query fails, "success" when the query succeeds
    "params": {
            "initFinish":       "XXXX"
    }
}
```

Heartbeat（heartBeat）

Reporting Method: Active reporting.

The property status is defined as follows:

- 0: Abnormal
- 1: Normal

The device actively reports this property whenever its status changes.

```
{
    "version":"1.0",
    "method":"post",
    "params": {
            "heartBeat":        "0"
    }
}
```

Product Model（productMode）

Reporting Method: Not supported for active reporting.

This property supports querying. The query format is as follows:

```
{
    "version":"1.0",
    "method":"get",
    "params": {
            "productMode":      "?"
    }
}
```

Query response format is as follows:

```
{
	"version":"1.0",
	"opt":	"get",
	"res":	"success" //"fail" when the query fails, "success" when the query succeeds
	"params": {
		"productMode":	"XXXX"
	}
}
```

Product ID（productId）

Reporting Method: Not supported for active reporting.

This property supports querying. The query format is as follows:

```
{
	"version":"1.0",
	"method":"get",
	"params": {
		"productId":	"?"
	}
}
```

Query response format is as follows:

```
{
	"version":"1.0",
	"opt":	"get",
	"res":	"success" //"fail" when the query fails, "success" when the query succeeds
	"params": {
		"productId":	"XXXX"
	}
}
```

Hardware Model（hardwareModel）

Reporting Method: Not supported for active reporting.

This property supports querying. The query format is as follows:

```
{
	"version":"1.0",
	"method":"get",
	"params": {
		"hardwareModel":	"?"
	}
}
```

Query response format is as follows:

```
{
	"version":"1.0",
	"opt":	"get",
	"res":	"success" //"fail" when the query fails, "success" when the query succeeds
	"params": {
		"hardwareModel":	"XXXX"
	}
}
```

WIFI Firmware Version（firmwareVersionWiFi）

The device actively reports this information when it powers on and connects to the server. The specific format is as follows:

```
{
	"version":"1.0",
	"method":"post",
	"params": {
		"firmwareVersionWiFi":	"xxxxxxx"
	}
}
```

This property supports querying. The query format is as follows:

```
{
	"version":"1.0",
	"method":"get",
	"params": {
		"firmwareVersionWiFi":	"?"
	}
}
```

Query response format is as follows:

```
{
	"version":"1.0",
	"opt":	"get",
	"res":	"success"  //"fail" when the query fails, "success" when the query succeeds
	"params": {
		"firmwareVersionWiFi":	"XXXX"
	}
}
```

Firmware Version（firmwareVersion）

Reporting Method: Active reporting. The device reports this property when it connects to the server.。

```
{
    "version":"1.0",
    "method":"post",
    "params": {
            "firmwareVersion":  "xxxx"
    }
}
```

This property supports querying. The query format is as follows:

```
{
    "version":"1.0",
    "method":"get",
    "params": {
            "firmwareVersion":  "?"
    }
}
```

Query response format is as follows:

```
{
    "version":"1.0",
    "opt":      "get",
    "res":      "success"  //"fail" when the query fails, "success" when the query succeeds
    "params": {
            "firmwareVersion":  "XXXX"
    }
}
```

Firmware Version（firmwareVersionProduct）

Reporting Method: Active reporting. The device reports this property when it connects to the server.。

```
{
    "version":"1.0",
    "method":"post",
    "params": {
                    "firmwareVersionProduct":
                    "YF_60GFL_tongyongWIFI_2024.1.3_V2.0.0"
    }
}
```

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                    "firmwareVersionProduct":      "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":       "get",
        "res":       "success"
        "params": {
                                    "firmwareVersionProduct":
                                   "YF_60GFL_tongyongWIFI_2024.1.3_V2.0.0"
        }
}
```

Install Height（installHeight）

Reporting Method: Not supported for active reporting.

- Value range: 170−310
- Unit: cm

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                    "installHeight":        "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":       "get",
      "res":         "success" //"fail" when the query fails, "success" when the query succeeds
        "params": {
                    "installHeight":        "1"
        }
}
```

This property supports configuration. The format is as follows:

```
{
        "version":"1.0",
        "method":"set",
        "params": {
                "installHeight":        "2"
        }
}
```

The configuration result format is as follows:

```
{
        "version":     "1.0",
        "opt":          "set",
      "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "installHeight":        "2"
        }
}
```

Position Out-of-Bounds Status（locationOutOfBounds） **Not Available Currently**

Reporting Method: Active reporting.

The property value is defined as follows:

- 0: Out of range
- 1: Within range

The device reports this property whenever its status changes.

```
{
        "version":"1.0",
        "method":"post",
        "params": {
                "locationOutOfBounds":          "0"
        }
}
```

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "locationOutOfBounds":          "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
      "res":        "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                    "locationOutOfBounds":        "1"
        }
}
```

Human Detection Function Switch（humanSwitch）

Reporting Method: Not supported for active reporting.

Value range:

- 1: Function enabled
- 0: Function disabled

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                    "humanSwitch":      "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
      "res":        "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                    "humanSwitch":      "1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
        "params": {
                    "humanSwitch":      "1"
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":          "set",
      "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                        "humanSwitch":       "1"
        }
}
```

Human Presence Status（someoneExists）

Reporting Method: Not supported for active reporting.

Value range:

- 1: Person detected
- 0: No person detected

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"post",
        "params": {
                        "someoneExists":     "1"   // Person detected in the current environment
        }
}
```

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                        "someoneExists":     "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":       "get",
      "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                        "someoneExists":     "1"
```

```
        }
    }
```

Human Motion Status（motionStatus）

Reporting Method: Active reporting.

The property value is defined as follows:

- 0: None
- 1: Stationary
- 2: Active

The device reports this property whenever its status changes.

```
{
        "version":"1.0",
        "method":"post",
        "params": {
                "motionStatus":       "1"     // Stationary
        }
}
```

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "motionStatus":       "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":       "get",
      "res":         "success" //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "motionStatus":       "1"
        }
}
```

Movement Signs Parameters（movementSigns）

Reporting Method: Active reporting.

- Value range: 0−100

The device reports this data periodically.

```
{
```

```
        "version":"1.0",
        "method":"post",
        "params": {
                "movementSigns":   "100"
        }
}
```

Sitting Horizontal Distance（sittingHorizontalDistance）

Reporting Method: Not supported for active reporting.

- Value range: 0−300 cm。

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "sittingHorizontalDistance":    "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
     "res":         "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "sittingHorizontalDistance":    "1"
        }
}
```

This property supports configuration. The format is as follows:

```
{
        "version":"1.0",
        "method":"set",
        "params": {
                "sittingHorizontalDistance":    "1"
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":         "set",
```

```
    "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
      "params": {
                    "sittingHorizontalDistance":    "1"
      }
}
```

Motion Horizontal Distance（horizontalDistanceOfMovement）

Reporting Method: Not supported for active reporting.

- Value range: 0−300 cm。

This property supports querying. The query format is as follows:

```
{
      "version":"1.0",
      "method":"get",
      "params": {
                    "horizontalDistanceOfMovement":          "?"
      }
}
```

Query response format is as follows:

```
{
      "version":"1.0",
      "opt":       "get",
    "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
      "params": {
                    "horizontalDistanceOfMovement":          "1"
      }
}
```

This property supports configuration. The format is as follows:

```
{
      "version":"1.0",
      "method":"set",
      "params": {
                    "horizontalDistanceOfMovement":          "1"
      }
}
```

The configuration result format is as follows:

```
{
      "version":        "1.0",
      "opt":          "set",
    "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
```

```
        "params": {
                "horizontalDistanceOfMovement":         "1"
        }
}
```

Human Presence Judgment Method（humanExistenceJudgmentMethod） Currently unavailable; reserved for future use.

Reporting Method: Not supported for active reporting.

The property value is 1 Byte.

- Value range: 0−1

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "humanExistenceJudgmentMethod":       "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
      "res":        "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "humanExistenceJudgmentMethod":       "1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
        "params": {
                "humanExistenceJudgmentMethod":       "1"
        }
}
```

The configuration result format is as follows:

```
{
        "version":       "1.0",
        "opt":         "set",
      "res":        "success"  //"fail" when the query fails, "success" when the query succeeds
```

```
        "params": {
                "humanExistenceJudgmentMethod":       "1"
        }
}
```

Human Presence Detection Threshold（humanPresenceJudgmentThreshold）

Reporting Method: Not supported for active reporting.

The property value is 4 Bytes.

- Value range: 0x00000000−0xFFFFFFFF

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "humanPresenceJudgmentThreshold":     "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":       "get",
      "res":         "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "humanPresenceJudgmentThreshold":     "50"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
        "params": {
                "humanPresenceJudgmentThreshold":     "50"
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":          "set",
      "res":         "success"  //"fail" when the query fails, "success" when the query succeeds
```

```
        "params": {
                "humanPresenceJudgmentThreshold":    "50"
        }
}
```

Human Presence Energy Value（humanPresenceEnergyValue）

Reporting Method: Active reporting.

- Value range: 0−100

The device reports this data periodically.

```
{
        "version":"1.0",
        "method":"post",
        "params": {
                "humanPresenceEnergyValue":              "40"
        }
}
```

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "humanPresenceEnergyValue":              "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
    "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "humanPresenceEnergyValue":              "50"
        }
}
```

Human Energy Value Switch（humanEnergyValueSwitch）

Reporting Method: Active reporting.

- Value range: 0−100

The device reports this data periodically.

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                    "humanEnergyValueSwitch":   "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
     "res":         "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                    "humanEnergyValueSwitch":   "1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
        "params": {
                    "humanEnergyValueSwitch":   "1"
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":          "set",
     "res":         "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                    "humanEnergyValueSwitch":   "1"
        }
}
```

No Presence Duration（unmannedTime）

Reporting Method: Not supported for active reporting.

The property value is 4 Bytes.

- Value range: 10−1800 s

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                    "unmannedTime":    "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":       "get",
      "res":         "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                    "unmannedTime":    "1"
        }
}
```

This property supports configuration. The format is as follows:

```
{
        "version":"1.0",
        "method":"set",
        "params": {
                    "unmannedTime":    "1"
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":          "set",
      "res":         "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                    "unmannedTime":    "1"
        }
}
```

Fall Height Threshold（fallingAndBreakingHeight）

Reporting Method: Not supported for active reporting.

- Value range: 0–150 cm

This property supports querying. The query format is as follows:

```
{
```

```
        "version":"1.0",
        "method":"get",
        "params": {
                "fallingAndBreakingHeight":  "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
      "res":        "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "fallingAndBreakingHeight":  "1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
        "params": {
                "fallingAndBreakingHeight":  "1"
        }
}
```

The configuration result format is as follows:

```
{
        "version":       "1.0",
        "opt":         "set",
      "res":        "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "fallingAndBreakingHeight":  "1"
        }
}
```

Fall Switch（fallSwitch）

Reporting Method: Not supported for active reporting.

Value range:

- 1: Function enabled
- 0: Function disabled

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
```

```
        "method":"get",
        "params": {
                "fallSwitch":           "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
    "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "fallSwitch":           "1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
        "params": {
                "fallSwitch":           "1" // Set to enabled
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":          "set",
    "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "fallSwitch":           "1"
        }
}
```

Fall Status（fallStatus）

Reporting Method: Active reporting.

The property value is defined as follows:

- 0: No fall detected
- 1: Fall detected

The device reports this property whenever its status changes.

```
{
        "version":"1.0",
```

```
        "method":"post",
        "params": {
                "fallStatus":           "100"
        }
}
```

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "fallStatus":           "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
      "res":        "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "fallStatus":           "1"          //Fall detected
        }
}
```

Stationary Presence Status（residentStatus）

Reporting Method: Active reporting.

The property value is defined as follows:

- 0: No stationary presence
- 1: Stationary presence detected

The device reports this property whenever its status changes.

```
{
        "version":"1.0",
        "method":"post",
        "params": {
                "residentStatus":      "1" //Stationary presence detected
        }
}
```

This property supports querying. The query format is as follows:

```
{
```

```
        "version":"1.0",
        "method":"get",
        "params": {
                "residentStatus":      "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
     "res":         "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "residentStatus":      "1"
        }
}
```

Stationary Presence Duration（residentWarningDuration）

Reporting Method: Not supported for active reporting.

- Value range: 0−65535
- Unit: s

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "residentWarningDuration":    "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
    "res":         "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "residentWarningDuration":    "1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
```

```
        "params": {
                "residentWarningDuration":    "2"
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":          "set",
      "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "residentWarningDuration":    "2"
        }
}
```

Stationary Presence Detection Switch（residentWarningDurationSwitch）

Reporting Method: Not supported for active reporting.

Value range:

- 1: Function enabled
- 0: Function disabled

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "residentWarningDurationSwitch":          "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":       "get",
        "res":       "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "residentWarningDurationSwitch":          "1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
```

```
        "params": {
                "residentWarningDurationSwitch":        "1" // Set to enabled
        }
}
```

The configuration response format is as follows:

```
{
        "version":      "1.0",
        "opt":      "set",
        "res":      "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "residentWarningDurationSwitch":        "1"
        }
}
```

Fall Duration（fallDuration）

Reporting Method: Not supported for active reporting.

- Value range: 0−65535
- Unit: s

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "fallDuration":      "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
    "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "fallDuration":      "1"
        }
}
```

This property supports configuration. The format is as follows:

```
{
        "version":"1.0",
        "method":"set",
        "params": {
```

```
                "fallDuration":        "2"
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":          "set",
      "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "fallDuration":        "2"
        }
}
```

Voice Function Switch（US518FunctionSwitch）

Reporting Method: Not supported for active reporting.

Value range:

- 1: Function enabled
- 0: Function disabled

The default setting is enabled.

When this function is enabled, the device can perform voice inquiries. When the function is disabled, the device directly reports the detected status.

This property supports both configuration and querying. The format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "US518FunctionSwitch": "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":       "get",
      "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "US518FunctionSwitch":   "1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
        "params": {
                "US518FunctionSwitch":"1" // Set to enabled
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":          "set",
      "res":          "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                "US518FunctionSwitch":   "1"
        }
}
```

Voice Learning Mode (US518LearningFunction)

Note: When setting this property, the device must be in the human presence detected state. Otherwise, the setting cannot be completed correctly, and the response value will be "nobody".

Reporting Method: Not supported for active reporting.

Value range:

- 1: Enter learning mode
- 0: Not in learning mode

The default status is 0.

Note: After the voice learning mode is triggered, the device must complete the learning process before it can be triggered again. Currently, the trigger frequency is limited to once within 60 seconds. After the 60-second period expires, the device actively reports the status.

This property supports querying. The query format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                "US518LearningFunction":      "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
```

```
        "opt":      "get",
    "res":          "success"
        "params": {
                    "US518LearningFunction":"1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
        "params": {
                    "US518LearningFunction":     "1"
        }
}
```

The configuration result format is as follows:

```
{
        "version":        "1.0",
        "opt":          "set",
    "res":          "success"
        "params": {

                    "US518LearningFunction":"1" //有人存在回复 1 或 0 无人回复 nobody

        }
}
```

Night Light Control Switch（nightLightSwitch）

Note: When setting this property, the device must be in the human presence detected state. Otherwise, the setting cannot be completed correctly, and the response value will be "nobody".

Reporting Method: Not supported for active reporting.

Value range:

- 1: Turn on the light
- 0: Turn off the light

This property supports both querying and configuration. The format is as follows:

```
{
        "version":"1.0",
        "method":"get",
        "params": {
                    "nightLightSwitch": "?"
        }
}
```

Query response format is as follows:

```
{
        "version":"1.0",
        "opt":      "get",
      "res":        "success"
        "params": {
                    "nightLightSwitch":"1"
        }
}
```

This property supports configuration. The format is as follows:

```
        {
        "version":"1.0",
        "method":"set",
        "params": {
                    "nightLightSwitch": "1"
        }
}
```

The configuration result format is as follows:

```
{
        "version":       "1.0",
        "opt":         "set",
      "res":        "success"
        "params": {
                    "nightLightSwitch": "1"
        }
}
```

Custom Protocol（custom_protocol）

Reporting Method: Active reporting.

- Value range: 0-1

The device reports this property immediately upon receiving radar data

```
{
        "version":"1.0",
        "method":"post",
        "params": {
                    "custom_protocol":  "1"
        // (53 59 60 60 00 01 01 6E 54 43   53 59 60 60 00 01 00 6D 54 43)
        }
}
```

3. Restricted Function Property Reporting

This function is mainly used for function properties that generate frequent active reporting data. It can be used to disable reporting for these properties or block specific function properties from being reported.

For each property, the corresponding value is defined as follows:

- 1: Reporting is disabled for this property
- 0: Reporting is enabled for this property

The setting commands with the **method** value of **"limit_set"** or the query commands with the **method** value of **"limit_get"** support configuring or querying multiple properties at the same time.

The query format for "Disable Reporting Data" is as follows:

```
{
    "version":"1.0",
    "method":"limit_get",
    "params": {
            "workDuration":     "?",
            "locationOutOfBounds":      "?",
            "someoneExists":    "?",
            "motionStatus":     "?",
            "movementSigns":    "?",
            "humanDistance":    "?",
            "humanPosition":    "?",
            "heartBeat":        "?",
            "proportionOfHeight":       "?"
    }
}
```

The response data format is as follows:

```
{
    "version":"1.0",
    "opt":      "limit_get",
    "res":      "success"  //"fail" when the query fails, "success" when the query succeeds
    "params": {
            "workDuration":     "0",
            "locationOutOfBounds":      "0",
            "someoneExists":    "0",
            "motionStatus":     "0",
            "movementSigns":    "0",
            "humanDistance":    "0",
            "humanPosition":    "0",
            "heartBeat":        "0",
            "proportionOfHeight":       "0"
    }
}
```

The configuration format for "Disable Reporting Data" is as follows:

```
{
    "version":"1.0",
    "method":"limit_set",
    "params": {
            "workDuration":     "0",
            "locationOutOfBounds":      "0",
            "someoneExists":    "0",
            "motionStatus":     "0",
            "movementSigns":    "0",
            "humanDistance":    "0",
            "humanPosition":    "0",
            "heartBeat":        "0",
            "proportionOfHeight":       "0"

    }
}
```

The response data format is as follows:

```
{
    "version":"1.0",
    "opt":      "limit_set",
    "res":      "success"  //"fail" when the query fails, "success" when the query succeeds
    "params": {
            "workDuration":     "0",
            "locationOutOfBounds":      "0",
            "someoneExists":    "0",
            "motionStatus":     "0",
            "movementSigns":    "0",
            "humanDistance":    "0",
            "humanPosition":    "0",
            "heartBeat":        "0",
            "proportionOfHeight":       "0"

    }
}
```

4. QoS (Quality of Service) Settings

The default QoS (Quality of Service) level is QoS 1.

The value definitions are as follows:

- 0: QoS 0
- 1: QoS 1
- 2: QoS 2

The query function for QoS (Quality of Service) is as follows:

```
{
        "version":"1.0",
        "method":"qos_get",
        "params": {
                        "Qos_post":             "?"
        }
}
```

The query response data format is as follows:

```
{
        "version":"1.0",
        "opt":      "qos_set",
        "res":      "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                        "Qos_post":             "0"
        }
}
```

The QoS (Quality of Service) configuration format is as follows:

```
{
        "version":"1.0",
        "method":"qos_set",
        "params": {
                        "Qos_post":             "0"
        }
}
```

The response data format is as follows:

```
{
        "version":"1.0",
        "opt":      "qos_set",
        "res":      "success"  //"fail" when the query fails, "success" when the query succeeds
        "params": {
                        "Qos_post":             "0"
        }
}
```

5. OTA Update

OTA Module Update（otaModule）

This property requires a command to specify the module to be upgraded.
Value definitions:

- 0: Wi-Fi module

- 1: Radar module
  The default value is 0.

  This control command must be sent before each OTA upgrade.。

```
{
    "version":"1.0",
    "method":"ota_set",
    "params": {
            "module":"0"
    }
}
```

OTA Update Information（otaInform）

The upgrade information sent to the device includes the firmware URL and port number. After receiving this information, the device downloads the firmware from the specified URL and port, and then starts the upgrade process.

If the upgrade fails, the device returns a failure response. After a successful upgrade, the module restarts and reports the updated firmware version.

The customer needs to set up and maintain their own web server for firmware hosting.

```
{
    "version":"1.0",
    "method":"ota_set",
    "params": {
        "otaInform":  {
            "firmwareUrl":  "http://192.168.31.88/app.rbl",
            "port":  "8090"  // Port number
          }
    }
}
```

升级失败返回格式如下：

```
{
    "version":"1.0",
    "opt":      "otaInform",
    "res":   "fail",
    "msg":   "ota failed!"
}
```

Update Progress（downloadProgress）

During the upgrade process, the device actively reports the upgrade progress.

- Value range: 0−100

  The specific format is as follows:

```
{
        "version":"1.0",
        "method":"ota_post",
        "params": {
                "downloadProgress":             "0"
        }
}
```

6. Historical Version Update Notes

Revision	Release Date	Summary
V1.0	~	Initial release
V1.1	2024/10/08	Removed some interface functions